



## ■ Features :

- Protections: Short circuit / Overload / Over voltage
- Cooling by free air convection
- · LED indicator for power on
- 100% full load burn-in test
- \* All using 105°C long life electrolytic capacitors
- \* Withstand 300VAC surge input for 5 second
- \* High operating temperature up to  $70^\circ\!\mathbb{C}$
- Withstand 5G vibration test
- High efficiency, long life and high reliability
- 3 years warranty

## **SPECIFICATION**



| MODEL                       |   | RT-125A   |   |             | RT-125B          |          |                  | RT-125C |                  |          | RT-125D |          |          |  |
|-----------------------------|---|---|---|-------------|------------------|----------|------------------|---------|------------------|----------|---------|----------|----------|--|
|                             | OUTPUT NUMBER   | CH1   | CH2   | CH3         | CH1              | CH2      | CH3              | CH1     | CH2              | CH3      | CH1     | CH2      | CH3      |  |
| OUTPUT                      | DC VOLTAGE  | 5V  | 12V   | -5V         | 5V               | 12V      | -12V             | 5V      | 15V              | -15V     | 5V      | 24V      | 12V      |  |
|                             | RATED CURRENT   | 12A   | 5.5A  | 1A          | 12A              | 5A       | 1A               | 10A     | 4.5A             | 1A       | 8A      | 3A       | 2A       |  |
|                             | CURRENT RANGE Note.6  | 2 ~ 15A   | 0.5 ~ 6A  | 0.1 ~ 1A    | 2 ~ 15A          | 0.5 ~ 6A | 0.1 ~ 1A         | 2 ~ 15A | 0.5 ~ 6A         | 0.1 ~ 1A | 2 ~ 15A | 0.4 ~ 4A | 0.1 ~ 2A |  |
|                             | RATED POWER Note.6  | 131W  |   |             | 132W             |          |                  | 132.5W  |                  |          | 136W    |          |          |  |
|                             | RIPPLE & NOISE (max.) Note.2  | 80mVp-p   | 120mVp-p  | 80mVp-p     | 80mVp-p          | 120mVp-p | 120mVp-p         | 80mVp-p | 150mVp-p         | 150mVp-p | 80mVp-p | 150mVp-p | 120mVp-  |  |
|                             | VOLTAGE ADJ. RANGE  | CH1: 4.75   | CH1: 4.75 ~ 5.5V  |             | CH1: 4.75 ~ 5.5V |          | CH1: 4.75 ~ 5.5V |         | CH1: 4.75 ~ 5.5V |          |         |          |          |  |
|                             | VOLTAGE TOLERANCE Note.3  | ±2.0%   | +8,-3%  | +6,-10%     | ±2.0%            | +8,-3%   | ±6.0%            | ±2.0%   | +8,-3%           | ±6.0%    | ±2.0%   | ±5.0%    | ±6.0%    |  |
|                             | LINE REGULATION Note.4  | ±0.5%   | ±1.0%   | ±1.0%       | ±0.5%            | ±1.0%    | ±1.0%            | ±0.5%   | ±1.0%            | ±1.0%    | ±0.5%   | ±1.0%    | ±1.0%    |  |
|                             | LOAD REGULATION Note.5  | ±1.0%   | ±3.0%   | ±6.0%       | ±1.0%            | ±3.0%    | ±6.0%            | ±1.0%   | ±3.0%            | ±6.0%    | ±1.0%   | ±3.0%    | ±6.0%    |  |
|                             | SETUP, RISE TIME  | 500ms, 20   | 500ms, 20ms/230VAC 1200ms, 30ms/115VAC at full load   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | HOLD UP TIME (Typ.)   | 25ms/230  | 25ms/230VAC 30ms/115VAC at full load  |             |                  |          |                  |         |                  |          |         |          |          |  |
| INPUT                       | VOLTAGE RANGE   | 88 ~ 132VAC / 176 ~ 264VAC selected by switch 248 ~ 373VDC(Withstand 300VAC surge for 5sec. Without damage)   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | FREQUENCY RANGE   | 47 ~ 63Hz   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | EFFICIENCY (Typ.)   | 79%   | 79%   |             |                  | 80%      |                  |         | 81%              |          |         | 82%      |          |  |
|                             | AC CURRENT (Typ.)   | 3A/115VA  | C 2A  | /230VAC     |                  |          |                  |         |                  |          |         |          |          |  |
|                             | INRUSH CURRENT (Typ.)   | COLD START 40A/230VAC   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | LEAKAGE CURRENT   | <2mA / 240VAC   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
| PROTECTION                  |   | 110 ~ 150% rated output power   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | OVERLOAD  | Protection type: Hiccup mode, recovers automatically after fault condition is removed   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             |   | CH1: 5.75 ~ 6.75V   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | OVER VOLTAGE  | Protection type: Hiccup mode, recovers automatically after fault condition is removed   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
| ENVIRONMENT                 | WORKING TEMP.   | -25 ~ +70   | °C (Refer t   | o "Derating | Curve")          |          |                  |         |                  |          |         |          |          |  |
|                             | WORKING HUMIDITY  | 20 ~ 90%  | 20 ~ 90% RH non-condensing  |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | STORAGE TEMP., HUMIDITY   | -40 ~ +85   | -40 ~ +85°C, 10 ~ 95% RH  |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | TEMP. COEFFICIENT   | ±0.03%/   | $\pm 0.03\%$ °C (0 ~ 50 °C)on +5V output  |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | VIBRATION   | 10 ~ 500H   | 10 ~ 500Hz, 5G 10min./1cycle, period for 60min. each along X, Y, Z axes                           |             |                  |          |                  |         |                  |          |         |          |          |  |
| SAFETY &<br>EMC<br>(Note 7) | SAFETY STANDARDS  | UL60950-1, TUV EN60950-1 approved   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | WITHSTAND VOLTAGE   | I/P-O/P:3KVAC I/P-FG:1.5KVAC O/P-FG:0.5KVAC   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | ISOLATION RESISTANCE  | I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C/ 70% RH   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | EMC EMISSION  | Compliance to EN55022 (CISPR22) Class B, EN61000-3-2,-3   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | EMC IMMUNITY  | Complian  | Compliance to EN61000-4-2,3,4,5,6,8,11, EN61000-6-2 (EN50082-2), heavy industry level, criteria A |             |                  |          |                  |         |                  |          |         |          |          |  |
| OTHERS                      | MTBF  | 209.3Khrs min. MIL-HDBK-217F (25°ℂ)   |   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | DIMENSION   | 199*98*3  | 199*98*38mm (L*W*H)   |             |                  |          |                  |         |                  |          |         |          |          |  |
|                             | PACKING   | 0.7Kg; 20   | 0.7Kg; 20pcs/14Kg/0.8CUFT   |             |                  |          |                  |         |                  |          |         |          |          |  |
| NOTE                        | Ripple & noise are measure     Tolerance : includes set up     Line regulation is measurec     Load regulation is measure     Each output can work within | lity mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature.  ed at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor.  tolerance, line regulation and load regulation.  d from low line to high line at rated load.  d from 20% to 100% rated load, and other output at 60% rated load.  n current range. But total output power can't exceed rated output power.  leared a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets |   |             |                  |          |                  |         |                  |          |         |          |          |  |

- 7. The power supply is considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets EMC directives. For guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies." (as available on http://www.meanwell.com)
- 8. Length of set up time is measured at cold first start. Turning ON/OFF the power supply very quickly may lead to increase of the set up time.



